

# Foxeer 3.3G VRX



**Feature:**

3.3G/40ch

Built-in Mic, Multi connector for video output & voltage input

CNC Heat Dissipation Shell

**Specification**

Items	Connector Type	Function
Voltage Input	DC2.5 port	DC 7-36V
Video Output	3.5mm headphone jack	CVBS
Voltage Input & Video Output	GH1.25-4P	for both Voltage Input & Video Output
Antenna Port	SMA	SMA
RF Sensitivity	-95dBm	-95dBm
Monitor	LCD monitor	Show band, Frequency

**VTx Frequency Table**

**Channel Frequency Table (in MHz)**

Channel	CH1	CH2	CH3	CH4	CH5	CH6	CH7	CH8
Band A	3320	3345	3370	3395	3420	3445	3470	3495
Band B	3310	3330	3355	3380	3405	3430	3455	3480
Band C	3490	3510	3530	3550	3570	3590	3610	3620
Band D	3330	3350	3370	3390	3410	3430	3450	3470
Band E	3170	3190	3210	3230	3250	3270	3290	3310

